

Signal Interface Control Document




for the

16-Channel CompactPCI Serial I/O Adapter

C²I² Systems Document No.	CCII/LCP/6-SICD/001
Document Issue	1.0
Issue Date	2011-08-22
Print Date	2011-08-22
File Name	W:\LCP\TECH\SICD\CLCSICD1.WPD
Distribution List No.	

© C²I² Systems *The copyright of this document is the property of C²I² Systems. The document is issued for the sole purpose for which it is supplied, on the express terms that it may not be copied in whole or part, used by or disclosed to others except as authorised in writing by C²I² Systems.*

Signature Sheet

Name	Signature	Date
Completed by <i>A. Davich</i>	 Electronic Technician Board-Level Products C ² P Systems	2011-08-22
Accepted by <i>W.D. Lumm</i>	 Project Manager Board-Level Products C ² P Systems	2011-08-22
Accepted by <i>H. C. H. METCALF</i>	 Quality Assurance C ² P Systems	2011-08-22

Abbreviations and Acronyms

CD	Carrier Detect
cPCI	Compact Peripheral Component Interconnect
CTS	Clear To Send
DSR	Data Set Ready
DTR	Data Terminal Ready
GND	Signal Ground
ICD	Interface Control Document
I/O	Input / Output
PCI	Peripheral Component Interconnect
PMC	PCI Mezzanine Card
RS-232	(Electronics Industries Association) Recommended Standard 232
RS-422	(Electronics Industries Association) Recommended Standard 422
RI	Ring Indicator
RTS	Request To Send
RxD	Received Data
SIO	Serial Input / Output
TxD	Transmitted Data

CCII/LCP/6-SICD/001	2011-08-22	Issue 1.0
CLCSICD1.WPD		Page iv of iv

1. **Scope**

1.1 Introduction

C²I² Systems manufactures and sells a family of Serial I/O Adapters in the PMC, PCI-104, PCI and cPCI formfactors. Certain versions of these adapters employ frontpanel I/O.

In such cases, a cable is required to provide physical access to the serial I/O signals available on the frontpanel connector of these serial I/O adapters and the corresponding serial data terminal equipment.

1.2 Scope

This document details the mapping of the signals required for the serial I/O cable assembly.

The I/O cable assembly consists of a 160-pin Molex connector (Part No. 71624-3000) on the adapter side which branches out into 16 cables of nominally 2,0 m in length with male DE-9 connectors on the terminal equipment side.

CCII/LCP/6-SICD/001	2011-08-22	Issue 1.0
CLCSICD1.WPD		Page 1 of 6

Cable Number : CCII/LCP/9-CCM/002

Used with Adapter : CCII/SIO/3CPCI/16PU/FP/COM

Configuration : Channels 1 to 8 : RS-232 DE-9 Male,
Channels 9 to 16 : RS-232 or RS-422 DE-9 Male

Pin No.	Connector J1 Signal Name Molex (71624-3000)	Pin No.	DE-9 Connector Signal Name
RS-232 (Channel 1)			
133	CD	1	Carrier Detect
147	RxD	2	Received Data
148	TxD	3	Transmitted Data
140	DTR	4	Data Terminal Ready
128	GND	5	Ground
139	DSR	6	Data Set Ready
146	RTS	7	Request To Send
145	CTS	8	Clear To Send
136	RI	9	Ring Indicator
RS-232 (Channel 2)			
130	CD	1	Carrier Detect
155	RxD	2	Received Data
156	TxD	3	Transmitted Data
138	DTR	4	Data Terminal Ready
127	GND	5	Ground
137	DSR	6	Data Set Ready
154	RTS	7	Request To Send
153	CTS	8	Clear To Send
131	RI	9	Ring Indicator
RS-232 (Channel 3)			
89	CD	1	Carrier Detect
118	RxD	2	Received Data
117	TxD	3	Transmitted Data
109	DTR	4	Data Terminal Ready
121	GND	5	Ground
110	DSR	6	Data Set Ready
119	RTS	7	Request To Send
120	CTS	8	Clear To Send
90	RI	9	Ring Indicator

Pin No.	Connector J1 Signal Name Molex (71624-3000)	Pin No.	DE-9 Connector Signal Name
RS-232 (Channel 4)			
93	CD	1	Carrier Detect
102	RxD	2	Received Data
101	TxD	3	Transmitted Data
111	DTR	4	Data Terminal Ready
122	GND	5	Ground
112	DSR	6	Data Set Ready
103	RTS	7	Request To Send
104	CTS	8	Clear To Send
94	RI	9	Ring Indicator
RS-232 (Channel 5)			
135	CD	1	Carrier Detect
150	RxD	2	Received Data
149	TxD	3	Transmitted Data
141	DTR	4	Data Terminal Ready
126	GND	5	Ground
142	DSR	6	Data Set Ready
151	RTS	7	Request To Send
152	CTS	8	Clear To Send
134	RI	9	Ring Indicator
RS-232 (Channel 6)			
132	CD	1	Carrier Detect
158	RxD	2	Received Data
157	TxD	3	Transmitted Data
143	DTR	4	Data Terminal Ready
125	GND	5	Ground
144	DSR	6	Data Set Ready
159	RTS	7	Request To Send
160	CTS	8	Clear To Send
129	RI	9	Ring Indicator
RS-232 (Channel 7)			
91	CD	1	Carrier Detect
115	RxD	2	Received Data
116	TxD	3	Transmitted Data
108	DTR	4	Data Terminal Ready
124	GND	5	Ground
107	DSR	6	Data Set Ready
114	RTS	7	Request To Send
113	CTS	8	Clear To Send
92	RI	9	Ring Indicator

Pin No.	Connector J1 Signal Name Molex (71624-3000)	Pin No.	DE-9 Connector Signal Name
RS-232 (Channel 8)			
95	CD	1	Carrier Detect
99	RxD	2	Received Data
100	TxD	3	Transmitted Data
106	DTR	4	Data Terminal Ready
123	GND	5	Ground
105	DSR	6	Data Set Ready
98	RTS	7	Request To Send
97	CTS	8	Clear To Send
96	RI	9	Ring Indicator
Channel 9			
RS-422			
17	TxD+	1	Transmitted Data +
18	TxD-	2	Transmitted Data -
20	RxD+	3	Received Data +
19	RxD-	4	Received Data -
RS-232			
60	GND	5	Ground
56	TxD	6	Transmitted Data
57	RxD	7	Received Data
58	RTS	8	Request To Send
59	CTS	9	Clear To Send
Channel 10			
RS-422			
12	TxD+	1	Transmitted Data +
13	TxD-	2	Transmitted Data -
15	RxD+	3	Received Data +
14	RxD-	4	Received Data -
RS-232			
55	GND	5	Ground
51	TxD	6	Transmitted Data
52	RxD	7	Received Data
53	RTS	8	Request To Send
54	CTS	9	Clear To Send

Pin No.	Connector J1 Signal Name Molex (71624-3000)	Pin No.	DE-9 Connector Signal Name
Channel 11			
RS-422			
7	TxD+	1	Transmitted Data +
8	TxD-	2	Transmitted Data -
10	RxD+	3	Received Data +
9	RxD-	4	Received Data -
RS-232			
45	GND	5	Ground
44	TxD	6	Transmitted Data
42	RxD	7	Received Data
43	RTS	8	Request To Send
41	CTS	9	Clear To Send
Channel 12			
RS-422			
5	TxD+	1	Transmitted Data +
4	TxD-	2	Transmitted Data -
2	RxD+	3	Received Data +
3	RxD-	4	Received Data -
RS-232			
50	GND	5	Ground
49	TxD	6	Transmitted Data
47	RxD	7	Received Data
48	RTS	8	Request To Send
46	CTS	9	Clear To Send
Channel 13			
RS-422			
25	TxD+	1	Transmitted Data +
24	TxD-	2	Transmitted Data -
22	RxD+	3	Received Data +
23	RxD-	4	Received Data -
RS-232			
65	GND	5	Ground
64	TxD	6	Transmitted Data
63	RxD	7	Received Data
62	RTS	8	Request To Send
61	CTS	9	Clear To Send

Pin No.	Connector J1 Signal Name Molex (71624-3000)	Pin No.	DE-9 Connector Signal Name
Channel 14			
RS-422			
30	TxD+	1	Transmitted Data +
29	TxD-	2	Transmitted Data -
27	RxD+	3	Received Data +
28	RxD-	4	Received Data -
RS-232			
70	GND	5	Ground
69	TxD	6	Transmitted Data
68	RxD	7	Received Data
67	RTS	8	Request To Send
66	CTS	9	Clear To Send
Channel 15			
RS-422			
37	TxD+	1	Transmitted Data +
38	TxD-	2	Transmitted Data -
40	RxD+	3	Received Data +
39	RxD-	4	Received Data -
RS-232			
75	GND	5	Ground
74	TxD	6	Transmitted Data
73	RxD	7	Received Data
72	RTS	8	Request To Send
71	CTS	9	Clear To Send
Channel 16			
RS-422			
32	TxD+	1	Transmitted Data +
33	TxD-	2	Transmitted Data -
35	RxD+	3	Received Data +
34	RxD-	4	Received Data -
RS-232			
80	GND	5	Ground
76	TxD	6	Transmitted Data
77	RxD	7	Received Data
78	RTS	8	Request To Send
79	CTS	9	Clear To Send